



EST Technology Co., Ltd.
Address: Chilingxiang, Qishantou, Santun, Houjie,
Dongguan, Guangdong, China
Tel: +86-769-83081888 Fax: +86-769-83081878

Ref. Report No.

ESTS-G19040802-M1

TEST REPORT

Energy Efficiency Regulations

Energy Efficiency of External Power Supplies

Applicant: Changzhou Baojin Electrical Equipment Co., Ltd
Address: Heshuchun, Lijia Town Changzhou Jiangsu 213165, P R China
Manufacturer: Same as applicant
Address: Same as applicant
Factory: Same as applicant
Address: Same as applicant
Product name: AC-AC ADAPTOR
Output Cord Length (cm): AC Terminal
Trade mark: --
Model No.: JXA-12V300-IP20, JXA-12V300-IP44
Ratings: Input: 120VAC, 60Hz, 0.28A;
Output: 12Vac, 0.3A
Standard: CEC: CALIFORNIA CODE OF REGULATIONS
Title 20. Public Utilities and Energy
Article 4. Appliance Efficiency Regulations
US DOE: Appendix Z to Subpart B of 10 CFR Part 430
Generic: Measurement of low power modes in accordance with IEC
62301:2011 and EN 50564: 2011
Date of Receiver: April 08, 2019
Date of Test: April 10, 2019
Date of Issue: March 31, 2022
Testing Laboratory: EST Technology Co., Ltd.
Address: Chilingxiang, Qishantou, Santun, Houjie, Dongguan, Guangdong,
China
Test Report No.....: ESTS-G19040802-M1
Test Result: PASS

This Test Report is Issued Under the Authority of:

Tested By

Joker Li

Joker Li/Engineer

Approved By

Jimmy Liang
Jimmy Liang/Reviewer

Test Report issued under the responsibility of:

EST Technology Co., Ltd.

Copy of marking plate(Representative):

The artwork below may be only a draft.



General product information:

1. The submitted samples were found to comply with the above standard.
2. This test results relate only to the submit samples.
3. Model JXA-12V300-IP20 was selected for testing.
4. The only difference between the two models is the model name, and everything else is the same.
5. -Report ESTS-G19040802,dated April 08, 2019 ,original report.
-Report ESTS-G19040802-M1,dated March 31, 2022,modification 1.
-Add model:JXA-12V300-IP44.

Note: This report shall not be reproduced except for authorized by testing laboratory.

General condition

1. Test Room

The test was carried out in a room that has an air speed close to the UUT of ≤ 0.5 m/s. The ambient temperature was maintained at $20^{\circ}\text{C} \pm 5^{\circ}\text{C}$ throughout the test.

2. Test Voltage

The input voltage is within the specified voltage $\pm 1\%$ and the specified frequency $\pm 1\%$. The UUT was tested at rated supply as mentioned in Summary of testing. The input power source is capable of delivering at least 10 times the nameplate input power of the UUT. The THD of the supply voltage when supplying the UUT in the specified mode was not exceeding 2%, up to and including the 13th harmonic.

3. Test Setup

The UUT was operated at 100% of rated current output for at least 30 minutes immediately prior to conducting efficiency measurements.

4. THD

The THD of the input voltage shall be ≤ 2 percent, up to and including the 13th harmonic. The crest factor of the input voltage shall be between 1.34 and 1.49.

5. Load Conditions

The UUT was tested at four active mode load conditions and the no-load condition according to table below by using electronic load.

Percentage of Nameplate Output Current	
Load Condition 1	$100\% \pm 2\%$
Load Condition 2	$75\% \pm 2\%$
Load Condition 3	$50\% \pm 2\%$
Load Condition 4	$25\% \pm 2\%$
Load Condition 5	0%

The 2% allowance is of nameplate output current, not of the calculated current value. For example, a UUT at Load Condition 3 may be tested in a range from 48% to 52% of rated output current.

International Efficiency Marking Protocol for External Power Supplies Version 3.0, September 2013

Mark	Performance Requirements				
	Nameplate Output Power (P _{no})	No-Load Mode Power	Nameplate Output Power (P _{no})	Average Efficiency in Active Mode	Power Factor
I	Used if none of the other criteria are met.				
II	0 to ≤ 10 watts	≤ 0.75	0 to < 1 watt	≥ 0.39 * P _{no}	Not applicable
	> 10 to 250 watts	≤ 1.0	1 to < 49 watts	≥ 0.107 x Ln(P _{no}) + 0.39	
			> 49 watts	≥ 0.82	
III	0 to < 10 watts	≤ 0.5	0 to 1 watt	≥ 0.49 * P _{no}	Not applicable
	10 to 250 watts	≤ 0.75	> 1 to < 49 watts	≥ 0.09 * Ln(P _{no}) + 0.49	
			>49 to 250 watts	≥ 0.84	
IV	0 to 250 watts	≤ 0.5	0 to 1 watt	≥ 0.5 * P _{no}	Not applicable
			1 to 51 watts	≥ 0.09 * Ln(P _{no}) + 0.5	
			>51 to 250 watts	≥ 0.85	
V	0 to < 50 watts	≤ 0.5 for ac-ac; ≤ 0.3 for ac-dc	0 to ≤ 1 watt	Standard: ≥ 0.480 *P _{no} + 0.140 Low Voltage: ≥0.497 * P _{no} + 0.067	EPSs with ≥ 100 watts input power must have a true power factor ≥ 0.9 at 100% of rated load when tested at 115 volts/60Hz.
	≥ 50 to ≤ 250 watts	≤ 0.5	> 1 to 49 watts	Standard: ≥ [0.0626* Ln(P _{no})] + 0.622 Low Voltage: ≥[0.0750 * Ln(P _{no})]+ 0.561	
			> 49 to 250 watts	Standard: ≥ 0.870 Low Voltage: ≥ 0.860	
VI	Single-Voltage				Not Applicable
	0 to ≤ 49 W	AC-DC: ≤ 0.100 AC-AC: ≤ 0.210	0 to ≤ 1 W	Basic Voltage: ≥ 0.5 * P _{no} + 0.16 Low Voltage: ≥ 0.517 * P _{no} + 0.087	
			1 to ≤ 49 W	Basic Voltage: ≥ 0.071* Ln(P _{no}) – 0.0014*P _{no} + 0.67 Low Voltage: ≥ 0.0834 * Ln(P _{no}) – 0.0014 * P _{no} + 0.609	
	>49 to ≤ 250 W	≤ 0.210	>49 to ≤ 250 W	Basic Voltage: ≥ 0.880 Low Voltage: ≥ 0.870	
	> 250 W	≤ 0.500	>250 W	≥ 0.875	
	Multiple-Voltage				
	Any	≤ 0.300	0 to ≤ 1 W	≥ 0.497 * P _{no} + 0.067	
			1 to ≤ 49 W	≥ 0.075 * Ln(P _{no}) + 0.561	
			>49 W	≥ 0.860	
VII	Reserved for future use				

Test data

Sample Model:JXA-12V300-IP20		115Vac/ 60Hz			
Load condition	No Load	Active load of the nameplate (12Vac, 0.3A)			
(Sample 1)	0%	25%	50%	75%	100%
Output voltage(Vac)	13.47	13.36	12.56	12.76	11.30
Output Current(mA)	--	75	150	225	300
Active Output Power(W)	--	1.00	1.88	2.87	3.39
Input Power(W)	0.140	1.24	2.27	3.48	4.62
Total Harmonic Distortion(THD,V%)	0.55	0.51	0.52	0.53	0.55
True Power Factor(W/VA)	0.168	0.954	0.963	0.982	0.993
Power Consumed(W)	0.14	0.24	0.39	0.61	1.23
Efficiency(%)	--	80.65	82.82	82.47	73.38
Average Efficiency(%)	--	79.83			
Load condition	No Load	Active load of the nameplate (12Vdc, 0.3A)			
(Sample 2)	0%	25%	50%	75%	100%
Output voltage(Vac)	13.52	13.32	12.54	12.89	12.01
Output Current(mA)	--	75	150	225	300
Active Output Power(W)	--	1.00	1.88	2.90	3.60
Input Power(W)	0.140	1.23	2.33	3.48	4.61
Total Harmonic Distortion(THD,V%)	51.00	0.55	0.56	0.55	0.52
True Power Factor(W/VA)	0.168	0.954	0.962	0.984	0.991
Power Consumed(W)	0.14	0.23	0.45	0.58	1.01
Efficiency(%)	--	81.30	80.69	83.33	78.09
Average Efficiency(%)	--	80.85			
Load condition	No Load	Active load of the nameplate (12Vdc, 0.3A)			
(Sample 3)	0%	25%	50%	75%	100%
Output voltage(Vac)	13.50	13.34	12.55	12.90	11.76
Output Current(mA)	--	75	150	225	300
Active Output Power(W)	--	1.00	1.88	2.90	3.53
Input Power(W)	0.140	1.24	2.26	3.48	4.60
Total Harmonic Distortion(THD,V%)	0.55	0.51	0.54	0.55	0.54
True Power Factor(W/VA)	0.168	0.952	0.967	0.991	0.993
Power Consumed(W)	0.14	0.24	0.38	0.58	1.07
Efficiency(%)	--	80.65	83.19	83.33	76.74
Average Efficiency(%)	--	80.98			

TEST RESULTS AND REQUIREMENT:

Test Results:

	Model No.	Test at 115V, 60Hz	Efficiency requirements
No load power (W)	JXA-12V300-IP20(#1)	0.14	≤ 0.21
	JXA-12V300-IP20(#2)	0.14	
	JXA-12V300-IP20(#3)	0.14	
Average Efficiency (%)	JXA-12V300-IP20(#1)	79.83	≥ 75.68
	JXA-12V300-IP20(#2)	80.85	
	JXA-12V300-IP20(#3)	80.98	
Verdict	---	PASS	---
Limit for efficiency mark level VI: Minimum Efficiency Average active mode efficiency limit greater than or equal to $\geq 0.071 * \ln(P_{no})$ $- 0.0014 * P_{no} + 0.67 = 0.7568$ The no-load condition consumption shall not exceed 0.21W.			

Photo documentation:



Photo 1



Photo 2

Equipments used for measurement

Test Equipments List					
Equipment Name	Manufacturer	Model #	Reg. No.	Cal. Date	Next Cal.
Digital Power Meter	YOKOGAWA	WT310	EST-S015-016	2021/5/22	2022/5/21
Digital Multimeter	FLUKE	Fluke17B	EST-S001-001	2021/5/22	2022/5/21
Meter ruler	Jieyang rongshen	7.5m	EST-S110-001	2021/5/29	2022/5/28
Temperature-Humidity Recorder	KTJ	TA218	EST-S019-001	2021/5/26	2022/5/25

-----End of Report-----